



**FM8038**



**FM12038**




**FM17251**




**200WZL**

Número de parte	Dimensiones (mm)	Voltaje (VCA)	Frecuencia (Hz)	Corriente (A)	Potencia (W)	RPM	Capacidad (m <sup>3</sup> /h)	Decibeles (CFM)	Decibeles (db(A))	Peso (g)	Rejilla de Seguridad
FM8038A1HSL	80x80x38	110	50/60	0.15/0.13	14/13	2400	44/51	26/30	28/31	340	PT0808
FM8038A2HSL	80x80x38	230	50/60	0.08/0.07	14/13	2400	44/51	26/30	28/31	340	PT0808
FM12038A1HSL	120x120x38	110	50/60	0.24/0.23	26/23	2700	153/170	90/100	42/46	500	PT1212
FM12038A2HSL	120x120x38	230	50/60	0.14/0.13	26/23	2700	153/170	90/100	42/46	500	PT1212
FM17251A1HSL	172x163x51	110	50/60	0.47/0.46	37/35	2400	255/289	150/170	52/53	950	PT1717
FM17251A2HSL	172x163x51	230	50/60	0.23/0.22	37/35	2400	255/289	150/170	52/53	950	PT1717
200WZL-2C	225x225x80	110	50/60	0.70	75	2600	1020	600	65	1920	PT2020
200WZL-2E	225x225x80	230	50/60	0.35	75	2600	1020	600	65	1920	PT2020
PF12038B24	120x120x38	24VCD	-	0.70	17	2500	162	95	40	250	PT1212


**Rejillas de Seguridad (opcional)**




**PT0808**



**PT1212**



**PT1717**



**PT2020**



**L5K13PUP211**  
Interrupor para puerta con actuador plastico